

# Hi-Reliability Optically Coupled Isolator



3C91C, 3C92C, 3N243, 3N244, 3N245, 3N261, 3N262, 3N263 (TX, TXV)



## Features:

- TO-72 hermetically sealed package
- 1 kVDC electrical isolation
- High current transfer ratio
- TX and TXV devices processed to MIL-PRF-19500

## Description:

Each device is a high reliability optically coupled isolator that consists of an infrared emitting diode and a NPN silicon phototransistor which are mounted in a hermetically sealed TO-72 package. The **3C91C** and **3C92C** have a 935 nm wavelength, whereas the **3N243**, **3N244**, **3N245**, **3N261**, **3N262** and **3N263** have an 880 nm wavelength. All devices have 0.50" (12.70 mm) leads. Electrical characteristics vary. The **3N261TX**, **3N262TX** and **3N263TX** devices are similar to JEDEC registered optically coupled isolators.

*TX and TXV devices are processed to OPTEK's military screening program patterned after MIL-PRF-19500.*

Please refer to Application Bulletins 208 and 210 for additional design information and reliability (degradation) data.


Contact your local representative or OPTEK for more information.

## Applications:


- High-voltage isolation between input and output
- Electrical isolation in dirty environments
- Industrial equipment
- Medical equipment
- Office equipment

| Part Number     | LED Peak Wavelength | Sensor     | Isolation Voltage (,000) | CTR Min / Max | I <sub>F</sub> (mA) Typ / Max | V <sub>CE</sub> (V) Typ / Max | Lead Length |
|-----------------|---------------------|------------|--------------------------|---------------|-------------------------------|-------------------------------|-------------|
| 3C91C (TX, TXV) | 935 nm              | Transistor | 1                        | 0.3 / 2.0     | 10 / 50                       | 10 / 50                       | 0.50"       |
| 3C92C (TX, TXV) |                     |            |                          |               |                               |                               |             |
| 3N243 (TX, TXV) | 0.15 / NA           |            |                          | 3 / 40        | 10 / 30                       |                               |             |
| 3N244 (TX, TXV) | 0.3 / NA            |            |                          |               |                               |                               |             |
| 3N245 (TX, TXV) | 0.6 / NA            |            |                          | 1 / 40        | 5 / 30                        |                               |             |
| 3N261 (TX, TXV) | .05 / NA            |            |                          |               |                               |                               |             |
| 3N262 (TX, TXV) | 1.0 / 5.0           |            |                          |               |                               |                               |             |
| 3N263 (TX, TXV) | 2.0 / 10.0          |            |                          |               |                               |                               |             |

Phototransistor Collector is connected to the Header-Base-Case for ALL versions



| Pin # | 3C91      | 3C92      | 3N2XX     |
|-------|-----------|-----------|-----------|
| 1     | Cathode   | Cathode   | Emitter   |
| 2     | Collector | Emitter   | Cathode   |
| 3     | Emitter   | Collector | Collector |
| 4     | Anode     | Anode     | Anode     |



## General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | Optek Technology, Inc.  
1645 Wallace Drive, Ste. 130, Carrollton, TX USA 75006 | Ph: +1 972 323 2200  
www.ttelectronics.com | sensors@ttelectronics.com

# Hi-Reliability Optically Coupled Isolator



## Absolute Maximum Ratings ( $T_A = 25^\circ\text{C}$ unless otherwise noted)

|                                                                                             |                                             |
|---------------------------------------------------------------------------------------------|---------------------------------------------|
| Operating Temperature Range                                                                 | $-55^\circ\text{C}$ to $+125^\circ\text{C}$ |
| Storage Temperature Range                                                                   | $-65^\circ\text{C}$ to $+150^\circ\text{C}$ |
| Input to Output Isolation Voltage                                                           | $\pm 1\text{ kVDC}^{(1)}$                   |
| Lead Soldering Temperature [1/16 inch (1.6 mm) from case for 5 seconds with soldering iron] | $260^\circ\text{C}^{(2)}$                   |

## Input Diode


|                    |                      |
|--------------------|----------------------|
| Forward DC Current | 40 mA                |
| Reverse Voltage    | 2.0 V                |
| Power Dissipation  | $60\text{ mW}^{(3)}$ |

## Output Phototransistor

|                              |                       |
|------------------------------|-----------------------|
| Continuous Collector Current | 30 mA                 |
| Collector-Emitter Voltage    | 30 V                  |
| Emitter-Collector Voltage    | 5.0 V                 |
| Power Dissipation            | $200\text{ mW}^{(4)}$ |

### Notes:

1. Measured with input leads shorted together and output leads shorted together.
2. RMA flux is recommended. Duration can be extended to 10 seconds maximum when flow soldering.
3. Derate linearly  $2.0\text{ mW}/^\circ\text{C}$  above  $25^\circ\text{C}$ .
4. Derate linearly  $0.60\text{ mW}/^\circ\text{C}$  above  $65^\circ\text{C}$ .



### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | Optek Technology, Inc.  
1645 Wallace Drive, Ste. 130, Carrollton, TX USA 75006 | Ph: +1 972 323 2200  
www.ttelectronics.com | sensors@ttelectronics.com

# Hi-Reliability Optically Coupled Isolator



## Electrical Characteristics ( $T_A = 25^\circ\text{C}$ unless otherwise noted)

| SYMBOL             | PARAMETER                                   | MIN | TYP | MAX | UNITS         | TEST CONDITIONS                                |
|--------------------|---------------------------------------------|-----|-----|-----|---------------|------------------------------------------------|
| <b>Input Diode</b> |                                             |     |     |     |               |                                                |
| $V_F$              | Forward Voltage                             |     |     |     |               |                                                |
|                    | 3C91C, 3C92C (TX, TXV)                      | -   | -   | 1.2 |               | $I_F = 2\text{ mA}$                            |
|                    | 3C91C, 3C92C (TX, TXV)                      | -   | -   | 1.5 |               | $I_F = 50\text{ mA}$                           |
|                    | 3N243, 3N244, 3N245 (TX, TXV)               | 0.8 | -   | 1.3 |               | $I_F = 10\text{ mA}$                           |
|                    | 3N243, 3N244, 3N245 (TX, TXV)               | 1.0 | -   | 1.5 | V             | $I_F = 10\text{ mA}, T_A = -55^\circ\text{C}$  |
|                    | 3N243, 3N244, 3N245 (TX, TXV)               | 0.7 | -   | 1.2 |               | $I_F = 10\text{ mA}, T_A = -100^\circ\text{C}$ |
|                    | 3N261, 3N262, 3N263 (TX, TXV)               | 0.8 | -   | 1.5 |               | $I_F = 10\text{ mA}$                           |
|                    | 3N261, 3N262, 3N263 (TX, TXV)               | 1.0 | -   | 1.7 |               | $I_F = 10\text{ mA}, T_A = -55^\circ\text{C}$  |
|                    | 3N261, 3N262, 3N263 (TX, TXV)               | 0.7 | -   | 1.3 |               | $I_F = 10\text{ mA}, T_A = -100^\circ\text{C}$ |
| $V_R$              | Reverse Voltage<br>3C91C, 3C92C (TX, TXV)   | 7   | -   | -   | V             | $I_R = 0.1\text{ mA}$                          |
| $I_R$              | Reverse Current                             |     |     |     |               |                                                |
|                    | 3C91C, 3C92C (TX, TXV)                      | -   | -   | 1   | $\mu\text{A}$ | $V_R = 3.0\text{ V}$                           |
|                    | 3N243, 3N244, 3N245 (TX, TXV)               | -   | -   | 100 |               | $V_R = 2.0\text{ V}$                           |
|                    | 3N261, 3N262, 3N263 (TX, TXV)               | -   | -   | 100 |               | $V_R = 2.0\text{ V}$                           |
| $C_{IN}$           | Diode Capacitance<br>3C91C, 3C92C (TX, TXV) | -   | 25  | -   | pF            | $V = 0, f = 1\text{ MHz}$                      |

## Output Phototransistor

|               |                                     |    |   |     |               |                                                   |
|---------------|-------------------------------------|----|---|-----|---------------|---------------------------------------------------|
| $V_{(BR)CEO}$ | Collector-Emitter Breakdown Voltage |    |   |     |               |                                                   |
|               | 3C91C, 3C92C (TX, TXV)              | 50 | - | -   |               | $I_C = 10.0\text{ mA}$                            |
|               | 3N243, 3N244, 3N245 (TX, TXV)       | 30 | - | -   | V             | $I_C = 1.0\text{ mA}$                             |
|               | 3N261, 3N262, 3N263 (TX, TXV)       | 40 | - | -   |               | $I_C = 1.0\text{ mA}$                             |
| $V_{(BR)ECO}$ | Emitter-Collector Breakdown Voltage |    |   |     |               |                                                   |
|               | 3C91C, 3C92C (TX, TXV)              | 7  | - | -   |               | $I_C = 10\text{ }\mu\text{A}$                     |
|               | 3N243, 3N244, 3N245 (TX, TXV)       | 5  | - | -   | V             | $I_E = 100\text{ }\mu\text{A}$                    |
|               | 3N261, 3N262, 3N263 (TX, TXV)       | 7  | - | -   |               | $I_E = 100\text{ }\mu\text{A}$                    |
| $I_{CEO}$     | Collector Dark Current              |    |   |     |               |                                                   |
|               | 3C91C, 3C92C (TX, TXV)              | -  | - | 10  | nA            | $V_{CE} = 5\text{ V}$                             |
|               | 3C91C, 3C92C (TX, TXV)              | -  | - | 50  | nA            | $V_{CE} = 50\text{ V}$                            |
|               | 3N243, 3N244, 3N245 (TX, TXV)       | -  | - | 100 | nA            | $V_{CE} = 10.0\text{ V}$                          |
|               | 3N243, 3N244, 3N245 (TX, TXV)       | -  | - | 100 | $\mu\text{A}$ | $V_{CE} = 10.0\text{ V}, T_A = 100^\circ\text{C}$ |
|               | 3N261, 3N262, 3N263 (TX, TXV)       | -  | - | 100 | $\mu\text{A}$ | $V_{CE} = 10.0\text{ V}$                          |
|               | 3N261, 3N262, 3N263 (TX, TXV)       | -  | - | 100 | $\mu\text{A}$ | $V_{CE} = 10.0\text{ V}, T_A = 100^\circ\text{C}$ |

### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | Optek Technology, Inc.  
1645 Wallace Drive, Ste. 130, Carrollton, TX USA 75006 | Ph: +1 972 323 2200  
www.ttelectronics.com | sensors@ttelectronics.com

# Hi-Reliability Optically Coupled Isolator



## Electrical Characteristics ( $T_A = 25^\circ\text{C}$ unless otherwise noted)

| SYMBOL         | PARAMETER                            | MIN | TYP | MAX | UNITS         | TEST CONDITIONS                                                              |
|----------------|--------------------------------------|-----|-----|-----|---------------|------------------------------------------------------------------------------|
| <b>Coupled</b> |                                      |     |     |     |               |                                                                              |
| $I_{C(ON)}$    | On-State Collector Current           |     |     |     |               |                                                                              |
|                | 3C91C, 3C92C (TX, TXV)               | 4.0 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 5\text{ V}$                                 |
|                | 3C91C, 3C92C (TX, TXV)               | 3.0 | -   | 20  |               | $I_F = 10\text{ mA}$ , $V_{CE} = 0.4\text{ V}$                               |
|                | 3N243 (TX, TXV)                      | 1.5 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$                              |
|                | 3N243 (TX, TXV)                      | 0.3 | -   | -   |               | $I_F = 3\text{ mA}$ , $V_{CE} = 10.0\text{ V}$                               |
|                | 3N243 (TX, TXV)                      | 0.5 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$ , $T_A = 55^\circ\text{ C}$  |
|                | 3N243 (TX, TXV)                      | 0.5 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$ , $T_A = 100^\circ\text{ C}$ |
|                | 3N244 (TX, TXV)                      | 3.0 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$                              |
|                | 3N244 (TX, TXV)                      | 0.8 | -   | -   |               | $I_F = 3\text{ mA}$ , $V_{CE} = 10.0\text{ V}$                               |
|                | 3N244 (TX, TXV)                      | 1.0 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$ , $T_A = 55^\circ\text{ C}$  |
|                | 3N244 (TX, TXV)                      | 1.0 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$ , $T_A = 100^\circ\text{ C}$ |
|                | 3N245 (TX, TXV)                      | 6.0 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$                              |
|                | 3N245 (TX, TXV)                      | 1.5 | -   | -   |               | $I_F = 3\text{ mA}$ , $V_{CE} = 10.0\text{ V}$                               |
|                | 3N245 (TX, TXV)                      | 1.5 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$ , $T_A = 55^\circ\text{ C}$  |
|                | 3N245 (TX, TXV)                      | 1.5 | -   | -   |               | $I_F = 10\text{ mA}$ , $V_{CE} = 10.0\text{ V}$ , $T_A = 100^\circ\text{ C}$ |
|                | 3N261 (TX, TXV)                      | 0.5 | -   | -   |               | $I_F = 1\text{ mA}$ , $V_{CE} = 5.0\text{ V}$                                |
|                | 3N261 (TX, TXV)                      | 0.7 | -   | -   |               | $I_F = 2.0\text{ mA}$ , $V_{CE} = 5.0\text{ V}$ , $T_A = 55^\circ\text{ C}$  |
|                | 3N261 (TX, TXV)                      | 0.5 | -   | -   |               | $I_F = 2.0\text{ mA}$ , $V_{CE} = 5.0\text{ V}$ , $T_A = 100^\circ\text{ C}$ |
|                | 3N262 (TX, TXV)                      | 1.0 | -   | 5   |               | $I_F = 1\text{ mA}$ , $V_{CE} = 5.0\text{ V}$                                |
|                | 3N262 (TX, TXV)                      | 1.4 | -   | -   |               | $I_F = 2.0\text{ mA}$ , $V_{CE} = 5.0\text{ V}$ , $T_A = 55^\circ\text{ C}$  |
|                | 3N262 (TX, TXV)                      | 1.0 | -   | -   |               | $I_F = 2.0\text{ mA}$ , $V_{CE} = 5.0\text{ V}$ , $T_A = 100^\circ\text{ C}$ |
|                | 3N263 (TX, TXV)                      | 2.0 | -   | 10  |               | $I_F = 1\text{ mA}$ , $V_{CE} = 5.0\text{ V}$                                |
|                | 3N263 (TX, TXV)                      | 2.8 | -   | -   |               | $I_F = 2.0\text{ mA}$ , $V_{CE} = 5.0\text{ V}$ , $T_A = 55^\circ\text{ C}$  |
|                | 3N263 (TX, TXV)                      | 2.0 | -   | -   |               | $I_F = 2.0\text{ mA}$ , $V_{CE} = 5.0\text{ V}$ , $T_A = 100^\circ\text{ C}$ |
| $V_{CE(SAT)}$  | Collector-Emitter Saturation Voltage |     |     |     |               |                                                                              |
|                | 3C91C, 3C92C (TX, TXV)               | -   | -   | 0.4 |               | $I_F = 50\text{ mA}$ , $I_C = 10\text{ mA}$                                  |
|                | 3N243, 3N244, 3N245 (TX, TXV)        | -   | -   | 0.3 |               | $I_F = 20\text{ mA}$ , $I_C = 1.50\text{ mA}$                                |
|                | 3N243, 3N244, 3N245 (TX, TXV)        | -   | -   | 0.3 |               | $I_F = 20\text{ mA}$ , $I_C = 3.0\text{ mA}$                                 |
|                | 3N243, 3N244, 3N245 (TX, TXV) 3N261, | -   | -   | 0.3 |               | $I_F = 20\text{ mA}$ , $I_C = 6.0\text{ mA}$                                 |
|                | 3N262, 3N263 (TX, TXV)               | -   | -   | 0.3 |               | $I_F = 2.0\text{ mA}$ , $I_C = 0.50\text{ mA}$                               |
|                | 3N261, 3N262, 3N263 (TX, TXV)        | -   | -   | 0.3 |               | $I_F = 2.0\text{ mA}$ , $I_C = 1.0\text{ mA}$                                |
| $t_{ON}$       | Turn-on Time                         |     |     |     |               |                                                                              |
|                | 3C91C, 3C92C (TX, TXV)               | -   | -   | 9   | $\mu\text{s}$ | $V_{CC} = 5\text{ V}$ , $I_C = 2\text{ mA}$ , $R_L = 100\ \Omega$            |
| $t_{OFF}$      | Turn-off Time                        |     |     |     |               |                                                                              |
|                | 3C91C, 3C92C (TX, TXV)               | -   | -   | 6   | $\mu\text{s}$ | $V_{CC} = 5\text{ V}$ , $I_C = 2\text{ mA}$ , $R_L = 100\ \Omega$            |

### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | Optek Technology, Inc.  
1645 Wallace Drive, Ste. 130, Carrollton, TX USA 75006 | Ph: +1 972 323 2200  
www.ttelectronics.com | sensors@ttelectronics.com

# Hi-Reliability Optically Coupled Isolator





## Electrical Characteristics ( $T_A = 25^\circ\text{C}$ unless otherwise noted)

| SYMBOL         | PARAMETER                                                                                                               | MIN    | TYP | MAX            | UNITS         | TEST CONDITIONS                                                                                                                                                                                                             |
|----------------|-------------------------------------------------------------------------------------------------------------------------|--------|-----|----------------|---------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Coupled</b> |                                                                                                                         |        |     |                |               |                                                                                                                                                                                                                             |
| $C_{IO}$       | Input-to-Output Capacitance<br>3C91C, 3C92C (TX, TXV)<br>3N243, 3N244, 3N245 (TX, TXV) 3N261,<br>3N262, 3N263 (TX, TXV) | -      | 2   | 2.5            | pF            | $f = 1\text{ MHz}$<br>$V_{IO} = 0\text{ V}, f = 1.00\text{ MHz}^{(1)}$<br>$V_{IO} = 0\text{ V}, f = 1.00\text{ MHz}^{(1)}$                                                                                                  |
| $I_{IO}$       | Leakage Input -to-Output<br>3N243, 3N244, 3N245 (TX, TXV) 3N261,<br>3N262, 3N263 (TX, TXV)                              | -      | -   | 100            | nA            | $V_{IO} = \pm 1.00\text{ kVDC}^{(1)}$<br>$V_{IO} = \pm 1.00\text{ kVDC}^{(1)}$                                                                                                                                              |
| $R_{IO}$       | Isolation Resistance<br>3C91C, 3C92C (TX, TXV)                                                                          | $10^9$ | -   | -              | $\Omega$      | $V_{IO} = +1\text{ kV}$                                                                                                                                                                                                     |
| $t_r$          | Output Rise Time<br>3N243, 3N244, 3N245 (TX, TXV)<br>3N261, 3N262 (TX, TXV)<br>3N263 (TX, TXV)                          | -      | -   | 10<br>20<br>25 | $\mu\text{s}$ | $V_{CC} = 10.0\text{ V}, I_F = 10.0\text{ mA}, R_L = 100\ \Omega^{(2)}$<br>$V_{CC} = 10.0\text{ V}, I_F = 5.0\text{ mA}, R_L = 100\ \Omega^{(2)}$<br>$V_{CC} = 10.0\text{ V}, I_F = 5.0\text{ mA}, R_L = 100\ \Omega^{(2)}$ |
| $t_f$          | Output Fall Time<br>3N243, 3N244, 3N245 (TX, TXV)<br>3N261, 3N262 (TX, TXV)<br>3N263 (TX, TXV)                          | -      | -   | 10<br>10<br>25 | $\mu\text{s}$ | $V_{CC} = 10.0\text{ V}, I_F = 10.0\text{ mA}, R_L = 100\ \Omega^{(2)}$<br>$V_{CC} = 10.0\text{ V}, I_F = 5.0\text{ mA}, R_L = 100\ \Omega^{(2)}$<br>$V_{CC} = 10.0\text{ V}, I_F = 5.0\text{ mA}, R_L = 100\ \Omega^{(2)}$ |

### Notes:

- Measured with input leads shorted together and output leads shorted together.
- The input waveform is supplied by a generator with the following characteristics:  $Z_{OUT} = 50\ \Omega$ ,  $t_r \leq 15\text{ ns}$ , duty cycle  $\sim 1\%$ , pulse width  $\sim 100\text{ ms}$



### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | Optek Technology, Inc.  
1645 Wallace Drive, Ste. 130, Carrollton, TX USA 75006 | Ph: +1 972 323 2200  
www.ttelectronics.com | sensors@ttelectronics.com