

# 74AUP1G80

Low-power D-type flip-flop; positive-edge trigger

Rev. 4 — 28 June 2012

Product data sheet

## 1. General description

The 74AUP1G80 provides the single positive-edge triggered D-type flip-flop. Information on the data input is transferred to the  $\bar{Q}$  output on the LOW-to-HIGH transition of the clock pulse. The input pin D must be stable one set-up time prior to the LOW-to-HIGH clock transition for predictable operation.

Schmitt trigger action at all inputs makes the circuit tolerant to slower input rise and fall times across the entire  $V_{CC}$  range from 0.8 V to 3.6 V.

This device ensures a very low static and dynamic power consumption across the entire  $V_{CC}$  range from 0.8 V to 3.6 V.

This device is fully specified for partial power-down applications using  $I_{OFF}$ .

The  $I_{OFF}$  circuitry disables the output, preventing the damaging backflow current through the device when it is powered down.

## 2. Features and benefits

- Wide supply voltage range from 0.8 V to 3.6 V
- High noise immunity
- Complies with JEDEC standards:
  - ◆ JESD8-12 (0.8 V to 1.3 V)
  - ◆ JESD8-11 (0.9 V to 1.65 V)
  - ◆ JESD8-7 (1.2 V to 1.95 V)
  - ◆ JESD8-5 (1.8 V to 2.7 V)
  - ◆ JESD8-B (2.7 V to 3.6 V)
- ESD protection:
  - ◆ HBM JESD22-A114F exceeds 5000 V
  - ◆ MM JESD22-A115-A exceeds 200 V
  - ◆ CDM JESD22-C101E exceeds 1000 V
- Low static power consumption;  $I_{CC} = 0.9 \mu A$  (maximum)
- Latch-up performance exceeds 100 mA per JESD 78 Class II
- Inputs accept voltages up to 3.6 V
- Low noise overshoot and undershoot < 10 % of  $V_{CC}$
- $I_{OFF}$  circuitry provides partial power-down mode operation
- Multiple package options
- Specified from  $-40^{\circ}C$  to  $+85^{\circ}C$  and  $-40^{\circ}C$  to  $+125^{\circ}C$

**nexperia**

### 3. Ordering information

Table 1. Ordering information

Type number	Package				Version
	Temperature range	Name	Description		
74AUP1G80GW	−40 °C to +125 °C	TSSOP5	plastic thin shrink small outline package; 5 leads; body width 1.25 mm		SOT353-1
74AUP1G80GM	−40 °C to +125 °C	XSON6	plastic extremely thin small outline package; no leads; 6 terminals; body 1 × 1.45 × 0.5 mm		SOT886
74AUP1G80GF	−40 °C to +125 °C	XSON6	plastic extremely thin small outline package; no leads; 6 terminals; body 1 × 1 × 0.5 mm		SOT891
74AUP1G80GN	−40 °C to +125 °C	XSON6	extremely thin small outline package; no leads; 6 terminals; body 0.9 × 1.0 × 0.35 mm		SOT1115
74AUP1G80GS	−40 °C to +125 °C	XSON6	extremely thin small outline package; no leads; 6 terminals; body 1.0 × 1.0 × 0.35 mm		SOT1202
74AUP1G80GX	−40 °C to +125 °C	X2SON5	X2SON5: plastic thermal enhanced extremely thin small outline package; no leads; 5 terminals; body 0.8 × 0.8 × 0.35 mm		SOT1226

### 4. Marking

Table 2. Marking

Type number	Marking code <sup>[1]</sup>
74AUP1G80GW	pT
74AUP1G80GM	pT
74AUP1G80GF	pT
74AUP1G80GN	pT
74AUP1G80GS	pT
74AUP1G80GX	pT

[1] The pin 1 indicator is located on the lower left corner of the device, below the marking code.

### 5. Functional diagram




Fig 1. Logic symbol




Fig 2. IEC logic symbol




Fig 3. Logic diagram

## 6. Pinning information

### 6.1 Pinning




Fig 4. Pin configuration SOT353-1




Fig 5. Pin configuration SOT886




Fig 6. Pin configuration SOT891, SOT1115 and SOT1202




Fig 7. Pin configuration SOT1226 (X2SON5)

## 6.2 Pin description

Table 3. Pin description

Symbol	Pin		Description
	TSSOP5 and X2SON5	XSON6	
D	1	1	data input
CP	2	2	clock pulse input
GND	3	3	ground (0 V)
$\bar{Q}$	4	4	data output
n.c.	-	5	not connected
$V_{CC}$	5	6	supply voltage

## 7. Functional description

Table 4. Function table<sup>[1]</sup>

Input		Output
CP	D	$\bar{Q}$
↑	L	H
↑	H	L
L	X	$\bar{q}$

[1] H = HIGH voltage level;

L = LOW voltage level;

↑ = LOW-to-HIGH CP transition;

X = don't care;

$\bar{q}$  = lower case letter indicates the state of referenced input, one set-up time prior to the LOW-to-HIGH CP transition.

## 8. Limiting values

Table 5. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Max	Unit
$V_{CC}$	supply voltage		-0.5	+4.6	V
$I_{IK}$	input clamping current	$V_I < 0$ V	-50	-	mA
$V_I$	input voltage		<sup>[1]</sup> -0.5	+4.6	V
$I_{OK}$	output clamping current	$V_O < 0$ V	-50	-	mA
$V_O$	output voltage	Active mode and Power-down mode	<sup>[1]</sup> -0.5	+4.6	V
$I_O$	output current	$V_O = 0$ V to $V_{CC}$	-	+20	mA
$I_{CC}$	supply current		-	50	mA
$I_{GND}$	ground current		-50	-	mA
$T_{stg}$	storage temperature		-65	+150	°C
$P_{tot}$	total power dissipation	$T_{amb} = -40$ °C to +125 °C	<sup>[2]</sup> -	250	mW

[1] The minimum input and output voltage ratings may be exceeded if the input and output current ratings are observed.

[2] For TSSOP5 packages: above 87.5 °C the value of  $P_{tot}$  derates linearly with 4.0 mW/K.

For XSON6 and X2SON5 packages: above 118 °C the value of  $P_{tot}$  derates linearly with 7.8 mW/K.

## 9. Recommended operating conditions

**Table 6. Recommended operating conditions**

Symbol	Parameter	Conditions	Min	Max	Unit
$V_{CC}$	supply voltage		0.8	3.6	V
$V_I$	input voltage		0	3.6	V
$V_O$	output voltage	Active mode and Power-down mode	0	3.6	V
$T_{amb}$	ambient temperature		-40	+125	°C
$\Delta t/\Delta V$	input transition rise and fall rate	$V_{CC} = 0.8 \text{ V to } 3.6 \text{ V}$	0	200	ns/V

## 10. Static characteristics

**Table 7. Static characteristics**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
<b><math>T_{amb} = 25 \text{ }^{\circ}\text{C}</math></b>						
$V_{IH}$	HIGH-level input voltage	$V_{CC} = 0.8 \text{ V}$	$0.70 \times V_{CC}$	-	-	V
		$V_{CC} = 0.9 \text{ V to } 1.95 \text{ V}$	$0.65 \times V_{CC}$	-	-	V
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	1.6	-	-	V
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	2.0	-	-	V
$V_{IL}$	LOW-level input voltage	$V_{CC} = 0.8 \text{ V}$	-	-	$0.30 \times V_{CC}$	V
		$V_{CC} = 0.9 \text{ V to } 1.95 \text{ V}$	-	-	$0.35 \times V_{CC}$	V
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	-	-	0.7	V
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	-	-	0.9	V
$V_{OH}$	HIGH-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = -20 \mu\text{A}; V_{CC} = 0.8 \text{ V to } 3.6 \text{ V}$	$V_{CC} - 0.1$	-	-	V
		$I_O = -1.1 \text{ mA}; V_{CC} = 1.1 \text{ V}$	$0.75 \times V_{CC}$	-	-	V
		$I_O = -1.7 \text{ mA}; V_{CC} = 1.4 \text{ V}$	1.11	-	-	V
		$I_O = -1.9 \text{ mA}; V_{CC} = 1.65 \text{ V}$	1.32	-	-	V
		$I_O = -2.3 \text{ mA}; V_{CC} = 2.3 \text{ V}$	2.05	-	-	V
		$I_O = -3.1 \text{ mA}; V_{CC} = 2.3 \text{ V}$	1.9	-	-	V
		$I_O = -2.7 \text{ mA}; V_{CC} = 3.0 \text{ V}$	2.72	-	-	V
		$I_O = -4.0 \text{ mA}; V_{CC} = 3.0 \text{ V}$	2.6	-	-	V
$V_{OL}$	LOW-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = 20 \mu\text{A}; V_{CC} = 0.8 \text{ V to } 3.6 \text{ V}$	-	-	0.1	V
		$I_O = 1.1 \text{ mA}; V_{CC} = 1.1 \text{ V}$	-	-	$0.3 \times V_{CC}$	V
		$I_O = 1.7 \text{ mA}; V_{CC} = 1.4 \text{ V}$	-	-	0.31	V
		$I_O = 1.9 \text{ mA}; V_{CC} = 1.65 \text{ V}$	-	-	0.31	V
		$I_O = 2.3 \text{ mA}; V_{CC} = 2.3 \text{ V}$	-	-	0.31	V
		$I_O = 3.1 \text{ mA}; V_{CC} = 2.3 \text{ V}$	-	-	0.44	V
		$I_O = 2.7 \text{ mA}; V_{CC} = 3.0 \text{ V}$	-	-	0.31	V
		$I_O = 4.0 \text{ mA}; V_{CC} = 3.0 \text{ V}$	-	-	0.44	V
$I_I$	input leakage current	$V_I = \text{GND to } 3.6 \text{ V}; V_{CC} = 0 \text{ V to } 3.6 \text{ V}$	-	-	$\pm 0.1$	$\mu\text{A}$

Table 7. Static characteristics ...continued

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$I_{OFF}$	power-off leakage current	$V_I$ or $V_O$ = 0 V to 3.6 V; $V_{CC}$ = 0 V	-	-	$\pm 0.2$	$\mu A$
$\Delta I_{OFF}$	additional power-off leakage current	$V_I$ or $V_O$ = 0 V to 3.6 V; $V_{CC}$ = 0 V to 0.2 V	-	-	$\pm 0.2$	$\mu A$
$I_{CC}$	supply current	$V_I$ = GND or $V_{CC}$ ; $I_O$ = 0 A; $V_{CC}$ = 0.8 V to 3.6 V	-	-	0.5	$\mu A$
$\Delta I_{CC}$	additional supply current	$V_I$ = $V_{CC}$ - 0.6 V; $I_O$ = 0 A; $V_{CC}$ = 3.3 V	[1]	-	40	$\mu A$
$C_I$	input capacitance	$V_{CC}$ = 0 V to 3.6 V; $V_I$ = GND or $V_{CC}$	-	1.5	-	$pF$
$C_O$	output capacitance	$V_O$ = GND; $V_{CC}$ = 0 V	-	3.0	-	$pF$
<b><math>T_{amb} = -40^{\circ}C</math> to <math>+85^{\circ}C</math></b>						
$V_{IH}$	HIGH-level input voltage	$V_{CC}$ = 0.8 V	$0.70 \times V_{CC}$	-	-	V
		$V_{CC}$ = 0.9 V to 1.95 V	$0.65 \times V_{CC}$	-	-	V
		$V_{CC}$ = 2.3 V to 2.7 V	1.6	-	-	V
		$V_{CC}$ = 3.0 V to 3.6 V	2.0	-	-	V
$V_{IL}$	LOW-level input voltage	$V_{CC}$ = 0.8 V	-	-	$0.30 \times V_{CC}$	V
		$V_{CC}$ = 0.9 V to 1.95 V	-	-	$0.35 \times V_{CC}$	V
		$V_{CC}$ = 2.3 V to 2.7 V	-	-	0.7	V
		$V_{CC}$ = 3.0 V to 3.6 V	-	-	0.9	V
$V_{OH}$	HIGH-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = -20 \mu A$ ; $V_{CC}$ = 0.8 V to 3.6 V	$V_{CC} - 0.1$	-	-	V
		$I_O = -1.1 \text{ mA}$ ; $V_{CC}$ = 1.1 V	$0.7 \times V_{CC}$	-	-	V
		$I_O = -1.7 \text{ mA}$ ; $V_{CC}$ = 1.4 V	1.03	-	-	V
		$I_O = -1.9 \text{ mA}$ ; $V_{CC}$ = 1.65 V	1.30	-	-	V
		$I_O = -2.3 \text{ mA}$ ; $V_{CC}$ = 2.3 V	1.97	-	-	V
		$I_O = -3.1 \text{ mA}$ ; $V_{CC}$ = 2.3 V	1.85	-	-	V
		$I_O = -2.7 \text{ mA}$ ; $V_{CC}$ = 3.0 V	2.67	-	-	V
$V_{OL}$	LOW-level output voltage	$I_O = -4.0 \text{ mA}$ ; $V_{CC}$ = 3.0 V	2.55	-	-	V
		$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = 20 \mu A$ ; $V_{CC}$ = 0.8 V to 3.6 V	-	-	0.1	V
		$I_O = 1.1 \text{ mA}$ ; $V_{CC}$ = 1.1 V	-	-	$0.3 \times V_{CC}$	V
		$I_O = 1.7 \text{ mA}$ ; $V_{CC}$ = 1.4 V	-	-	0.37	V
		$I_O = 1.9 \text{ mA}$ ; $V_{CC}$ = 1.65 V	-	-	0.35	V
		$I_O = 2.3 \text{ mA}$ ; $V_{CC}$ = 2.3 V	-	-	0.33	V
		$I_O = 3.1 \text{ mA}$ ; $V_{CC}$ = 2.3 V	-	-	0.45	V
$I_I$	input leakage current	$I_O = 2.7 \text{ mA}$ ; $V_{CC}$ = 3.0 V	-	-	0.33	V
		$I_O = 4.0 \text{ mA}$ ; $V_{CC}$ = 3.0 V	-	-	0.45	V
$I_{OFF}$	power-off leakage current	$V_I$ = GND to 3.6 V; $V_{CC}$ = 0 V to 3.6 V	-	-	$\pm 0.5$	$\mu A$
$\Delta I_{OFF}$	additional power-off leakage current	$V_I$ or $V_O$ = 0 V to 3.6 V; $V_{CC}$ = 0 V	-	-	$\pm 0.5$	$\mu A$
		$V_I$ or $V_O$ = 0 V to 3.6 V; $V_{CC}$ = 0 V to 0.2 V	-	-	$\pm 0.6$	$\mu A$

Table 7. Static characteristics ...continued

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$I_{CC}$	supply current	$V_I = GND$ or $V_{CC}$ ; $I_O = 0 A$ ; $V_{CC} = 0.8 V$ to $3.6 V$	-	-	0.9	$\mu A$
$\Delta I_{CC}$	additional supply current	$V_I = V_{CC} - 0.6 V$ ; $I_O = 0 A$ ; $V_{CC} = 3.3 V$	[1]	-	50	$\mu A$
<b><math>T_{amb} = -40^{\circ}C</math> to <math>+125^{\circ}C</math></b>						
$V_{IH}$	HIGH-level input voltage	$V_{CC} = 0.8 V$	$0.75 \times V_{CC}$	-	-	V
		$V_{CC} = 0.9 V$ to $1.95 V$	$0.70 \times V_{CC}$	-	-	V
		$V_{CC} = 2.3 V$ to $2.7 V$	1.6	-	-	V
		$V_{CC} = 3.0 V$ to $3.6 V$	2.0	-	-	V
$V_{IL}$	LOW-level input voltage	$V_{CC} = 0.8 V$	-	-	$0.25 \times V_{CC}$	V
		$V_{CC} = 0.9 V$ to $1.95 V$	-	-	$0.30 \times V_{CC}$	V
		$V_{CC} = 2.3 V$ to $2.7 V$	-	-	0.7	V
		$V_{CC} = 3.0 V$ to $3.6 V$	-	-	0.9	V
$V_{OH}$	HIGH-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = -20 \mu A$ ; $V_{CC} = 0.8 V$ to $3.6 V$	$V_{CC} - 0.11$	-	-	V
		$I_O = -1.1 mA$ ; $V_{CC} = 1.1 V$	$0.6 \times V_{CC}$	-	-	V
		$I_O = -1.7 mA$ ; $V_{CC} = 1.4 V$	0.93	-	-	V
		$I_O = -1.9 mA$ ; $V_{CC} = 1.65 V$	1.17	-	-	V
		$I_O = -2.3 mA$ ; $V_{CC} = 2.3 V$	1.77	-	-	V
		$I_O = -3.1 mA$ ; $V_{CC} = 2.3 V$	1.67	-	-	V
		$I_O = -2.7 mA$ ; $V_{CC} = 3.0 V$	2.40	-	-	V
		$I_O = -4.0 mA$ ; $V_{CC} = 3.0 V$	2.30	-	-	V
$V_{OL}$	LOW-level output voltage	$V_I = V_{IH}$ or $V_{IL}$				
		$I_O = 20 \mu A$ ; $V_{CC} = 0.8 V$ to $3.6 V$	-	-	0.11	V
		$I_O = 1.1 mA$ ; $V_{CC} = 1.1 V$	-	-	$0.33 \times V_{CC}$	V
		$I_O = 1.7 mA$ ; $V_{CC} = 1.4 V$	-	-	0.41	V
		$I_O = 1.9 mA$ ; $V_{CC} = 1.65 V$	-	-	0.39	V
		$I_O = 2.3 mA$ ; $V_{CC} = 2.3 V$	-	-	0.36	V
		$I_O = 3.1 mA$ ; $V_{CC} = 2.3 V$	-	-	0.50	V
		$I_O = 2.7 mA$ ; $V_{CC} = 3.0 V$	-	-	0.36	V
		$I_O = 4.0 mA$ ; $V_{CC} = 3.0 V$	-	-	0.50	V
$I_I$	input leakage current	$V_I = GND$ to $3.6 V$ ; $V_{CC} = 0 V$ to $3.6 V$	-	-	$\pm 0.75$	$\mu A$
$I_{OFF}$	power-off leakage current	$V_I$ or $V_O = 0 V$ to $3.6 V$ ; $V_{CC} = 0 V$	-	-	$\pm 0.75$	$\mu A$
$\Delta I_{OFF}$	additional power-off leakage current	$V_I$ or $V_O = 0 V$ to $3.6 V$ ; $V_{CC} = 0 V$ to $0.2 V$	-	-	$\pm 0.75$	$\mu A$
$I_{CC}$	supply current	$V_I = GND$ or $V_{CC}$ ; $I_O = 0 A$ ; $V_{CC} = 0.8 V$ to $3.6 V$	-	-	1.4	$\mu A$
$\Delta I_{CC}$	additional supply current	$V_I = V_{CC} - 0.6 V$ ; $I_O = 0 A$ ; $V_{CC} = 3.3 V$	[1]	-	75	$\mu A$

[1] One input at  $V_{CC} - 0.6 V$ , other input at  $V_{CC}$  or GND.

## 11. Dynamic characteristics

**Table 8. Dynamic characteristics**

Voltages are referenced to GND (ground = 0 V; for test circuit see [Figure 10](#))

Symbol	Parameter	Conditions	25 °C			−40 °C to +125 °C			Unit	
			Min	Typ <sup>[1]</sup>	Max	Min (85 °C)	Max (85 °C)	Min (125 °C)		
<b>C<sub>L</sub> = 5 pF</b>										
t <sub>pd</sub>	propagation delay	CP to $\overline{Q}$ ; see <a href="#">Figure 8</a>	<sup>[2]</sup>							
		V <sub>CC</sub> = 0.8 V	-	20.9	-	-	-	-	ns	
		V <sub>CC</sub> = 1.1 V to 1.3 V	2.9	6.0	12.9	2.6	14.3	2.6	15.7	
		V <sub>CC</sub> = 1.4 V to 1.6 V	1.9	4.2	7.6	2.0	8.9	2.0	9.8	
		V <sub>CC</sub> = 1.65 V to 1.95 V	1.7	3.4	5.9	1.6	7.0	1.6	7.7	
		V <sub>CC</sub> = 2.3 V to 2.7 V	1.4	2.6	4.3	1.2	5.6	1.2	6.2	
f <sub>max</sub>	maximum frequency	CP; see <a href="#">Figure 9</a>								
		V <sub>CC</sub> = 0.8 V	-	53	-	-	-	-	MHz	
		V <sub>CC</sub> = 1.1 V to 1.3 V	-	203	-	170	-	170	-	
		V <sub>CC</sub> = 1.4 V to 1.6 V	-	347	-	310	-	300	-	
		V <sub>CC</sub> = 1.65 V to 1.95 V	-	435	-	400	-	390	-	
		V <sub>CC</sub> = 2.3 V to 2.7 V	-	550	-	490	-	480	-	
<b>C<sub>L</sub> = 10 pF</b>										
t <sub>pd</sub>	propagation delay	CP to $\overline{Q}$ ; see <a href="#">Figure 8</a>	<sup>[2]</sup>							
		V <sub>CC</sub> = 0.8 V	-	24.6	-	-	-	-	ns	
		V <sub>CC</sub> = 1.1 V to 1.3 V	3.3	6.9	14.9	3.0	16.5	3.0	18.1	
		V <sub>CC</sub> = 1.4 V to 1.6 V	2.6	4.8	8.8	2.3	10.3	2.3	11.3	
		V <sub>CC</sub> = 1.65 V to 1.95 V	2.3	3.9	6.8	2.0	8.1	2.0	8.9	
		V <sub>CC</sub> = 2.3 V to 2.7 V	1.9	3.1	5.1	1.7	6.3	1.7	6.9	
f <sub>max</sub>	maximum frequency	CP; see <a href="#">Figure 9</a>								
		V <sub>CC</sub> = 0.8 V	-	52	-	-	-	-	MHz	
		V <sub>CC</sub> = 1.1 V to 1.3 V	-	192	-	150	-	150	-	
		V <sub>CC</sub> = 1.4 V to 1.6 V	-	324	-	280	-	230	-	
		V <sub>CC</sub> = 1.65 V to 1.95 V	-	421	-	310	-	250	-	
		V <sub>CC</sub> = 2.3 V to 2.7 V	-	486	-	370	-	360	-	
<b>74AUP1G80</b>										
All information provided in this document is subject to legal disclaimers.										
© Nexperia B.V. 2017. All rights reserved										
Product data sheet			Rev. 4 — 28 June 2012				8 of 22			

Table 8. Dynamic characteristics ...continued

Voltages are referenced to GND (ground = 0 V; for test circuit see [Figure 10](#)

Symbol	Parameter	Conditions	25 °C			−40 °C to +125 °C				Unit
			Min	Typ <sup>[1]</sup>	Max	Min (85 °C)	Max (85 °C)	Min (125 °C)	Max (125 °C)	
<b><math>C_L = 15 \text{ pF}</math></b>										
$t_{pd}$	propagation delay	CP to $\bar{Q}$ ; see <a href="#">Figure 8</a>	<sup>[2]</sup>							
		$V_{CC} = 0.8 \text{ V}$	-	28.2	-	-	-	-	-	ns
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	3.0	7.6	16.7	3.4	18.6	3.4	20.5	ns
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	3.0	5.3	9.8	2.6	11.5	2.6	12.7	ns
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	2.6	4.4	7.6	2.3	9.1	2.3	10.0	ns
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	2.2	3.5	5.7	2.0	6.9	2.0	7.6	ns
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	1.9	3.1	5.0	1.8	5.5	1.8	6.1	ns
$f_{max}$	maximum frequency	CP; see <a href="#">Figure 9</a>								
		$V_{CC} = 0.8 \text{ V}$	-	50	-	-	-	-	-	MHz
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	-	181	-	120	-	120	-	MHz
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	-	301	-	190	-	160	-	MHz
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	-	407	-	240	-	190	-	MHz
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	-	422	-	300	-	270	-	MHz
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	-	481	-	320	-	300	-	MHz
<b><math>C_L = 30 \text{ pF}</math></b>										
$t_{pd}$	propagation delay	CP to $\bar{Q}$ ; see <a href="#">Figure 8</a>	<sup>[2]</sup>							
		$V_{CC} = 0.8 \text{ V}$	-	38.8	-	-	-	-	-	ns
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	4.9	9.8	20.7	4.4	24.7	4.4	27.2	ns
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	4.0	6.8	12.7	3.5	15.0	3.5	16.5	ns
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	3.5	5.6	9.9	2.2	11.9	2.2	13.0	ns
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	3.1	4.5	7.5	2.8	9.3	2.8	10.2	ns
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	2.9	4.1	6.4	2.7	7.5	2.7	8.3	ns
$f_{max}$	maximum frequency	CP; see <a href="#">Figure 9</a>								
		$V_{CC} = 0.8 \text{ V}$	-	28	-	-	-	-	-	MHz
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	-	128	-	70	-	70	-	MHz
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	-	206	-	120	-	110	-	MHz
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	-	262	-	150	-	120	-	MHz
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	-	269	-	190	-	170	-	MHz
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	-	309	-	200	-	190	-	MHz
<b><math>C_L = 5 \text{ pF}, 10 \text{ pF}, 15 \text{ pF} \text{ and } 30 \text{ pF}</math></b>										
$t_{su(H)}$	set-up time HIGH	D to CP; see <a href="#">Figure 9</a>								
		$V_{CC} = 0.8 \text{ V}$	-	2.5	-	-	-	-	-	ns
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	-	0.5	-	2.2	-	2.2	-	ns
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	-	0.3	-	1.1	-	1.1	-	ns
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	-	0.3	-	0.8	-	0.8	-	ns
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	-	0.2	-	0.6	-	0.6	-	ns
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	-	0.2	-	0.4	-	0.4	-	ns

Table 8. Dynamic characteristics ...continued

Voltages are referenced to GND (ground = 0 V; for test circuit see [Figure 10](#)


Symbol	Parameter	Conditions	25 °C			−40 °C to +125 °C			Unit
			Min	Typ <sup>[1]</sup>	Max	Min (85 °C)	Max (85 °C)	Min (125 °C)	
$t_{su(L)}$	set-up time LOW	D to CP; see <a href="#">Figure 9</a>							
		$V_{CC} = 0.8 \text{ V}$	-	1.7	-	-	-	-	ns
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	-	0.3	-	2.0	-	2.0	-
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	-	0.2	-	1.3	-	1.3	-
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	-	0.2	-	1.1	-	1.1	-
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	-	0.3	-	0.8	-	0.8	-
$t_h$	hold time	D to CP; see <a href="#">Figure 9</a>							
		$V_{CC} = 0.8 \text{ V}$	-	-2.1	-	-	-	-	ns
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	-	-0.4	-	0.2	-	0.2	-
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	-	-0.3	-	0.1	-	0.1	-
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	-	-0.2	-	0	-	0	-
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	-	-0.2	-	0	-	0	-
$t_w$	pulse width	CP HIGH or LOW; see <a href="#">Figure 9</a>							
		$V_{CC} = 0.8 \text{ V}$	-	5.2	-	-	-	-	ns
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	-	1.0	-	3.0	-	3.0	-
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	-	0.8	-	2.0	-	2.0	-
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	-	0.6	-	2.0	-	2.0	-
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	-	0.5	-	2.0	-	2.0	-
$C_{PD}$	power dissipation capacitance	$f_i = 1 \text{ MHz};$ $V_i = \text{GND to } V_{CC}$	<sup>[3]</sup>						
		$V_{CC} = 0.8 \text{ V}$	-	1.8	-	-	-	-	pF
		$V_{CC} = 1.1 \text{ V to } 1.3 \text{ V}$	-	1.8	-	-	-	-	pF
		$V_{CC} = 1.4 \text{ V to } 1.6 \text{ V}$	-	1.9	-	-	-	-	pF
		$V_{CC} = 1.65 \text{ V to } 1.95 \text{ V}$	-	2.0	-	-	-	-	pF
		$V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$	-	2.4	-	-	-	-	pF
		$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}$	-	2.9	-	-	-	-	pF

[1] All typical values are measured at nominal  $V_{CC}$ .[2]  $t_{pd}$  is the same as  $t_{PLH}$  and  $t_{PHL}$ .[3]  $C_{PD}$  is used to determine the dynamic power dissipation ( $P_D$  in  $\mu\text{W}$ ). $P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \Sigma(C_L \times V_{CC}^2 \times f_o)$  where: $f_i$  = input frequency in MHz; $f_o$  = output frequency in MHz; $C_L$  = output load capacitance in pF; $V_{CC}$  = supply voltage in V;

N = number of inputs switching;

 $\Sigma(C_L \times V_{CC}^2 \times f_o)$  = sum of the outputs.


## 12. Waveforms



Measurement points are given in [Table 9](#).

Logic levels:  $V_{OL}$  and  $V_{OH}$  are typical output voltage drop that occur with the output load.

**Fig 8. The clock input (CP) to output ( $\bar{Q}$ ) propagation delays**




Measurement points are given in [Table 9](#).

Logic levels:  $V_{OL}$  and  $V_{OH}$  are typical output voltage drop that occur with the output load.

**Fig 9. The clock input (CP) to output ( $\bar{Q}$ ) propagation delays, clock pulse width, D to CP set-up and hold times and the maximum input clock frequency**

**Table 9. Measurement points**

Supply voltage	Output	Input		
$V_{CC}$ 0.8 V to 3.6 V	$V_M$ $0.5 \times V_{CC}$	$V_M$ $0.5 \times V_{CC}$	$V_I$ $V_{CC}$	$t_r = t_f$ $\leq 3.0 \text{ ns}$



001aac521

Test data is given in [Table 10](#).

Definitions for test circuit:

$R_L$  = Load resistance.

$C_L$  = Load capacitance including jig and probe capacitance.

$R_T$  = Termination resistance should be equal to the output impedance  $Z_0$  of the pulse generator.

$V_{EXT}$  = External voltage for measuring switching times.

**Fig 10. Test circuit for measuring switching times**

**Table 10. Test data**

Supply voltage	Load		$V_{EXT}$		
$V_{CC}$	$C_L$	$R_L$ <sup>[1]</sup>	$t_{PLH}, t_{PHL}$	$t_{PZH}, t_{PHZ}$	$t_{PZL}, t_{PLZ}$
0.8 V to 3.6 V	5 pF, 10 pF, 15 pF and 30 pF	5 kΩ or 1 MΩ	open	GND	$2 \times V_{CC}$

[1] For measuring enable and disable times  $R_L = 5 \text{ k}\Omega$ , for measuring propagation delays, setup and hold times and pulse width  $R_L = 1 \text{ M}\Omega$ .

## 13. Package outline

TSSOP5: plastic thin shrink small outline package; 5 leads; body width 1.25 mm

SOT353-1




Fig 11. Package outline SOT353-1 (TSSOP5)

XSON6: plastic extremely thin small outline package; no leads; 6 terminals; body  $1 \times 1.45 \times 0.5$  mm

SOT886





Fig 12. Package outline SOT886 (XSON6)

XSON6: plastic extremely thin small outline package; no leads; 6 terminals; body 1 x 1 x 0.5 mm

SOT891



## DIMENSIONS (mm are the original dimensions)

UNIT	A max	A1 max	b	D	E	e	e1	L	L1
mm	0.5	0.04	0.20 0.12	1.05 0.95	1.05 0.95	0.55	0.35	0.35 0.27	0.40 0.32

## Note

1. Can be visible in some manufacturing processes.

OUTLINE VERSION	REFERENCES				EUROPEAN PROJECTION	ISSUE DATE
	IEC	JEDEC	JEITA			
SOT891						05-04-06 07-05-15

Fig 13. Package outline SOT891 (XSON6)

**XSON6: extremely thin small outline package; no leads;  
6 terminals; body 0.9 x 1.0 x 0.35 mm**

SOT1115




Fig 14. Package outline SOT1115 (XSON6)

**XSON6: extremely thin small outline package; no leads;  
6 terminals; body 1.0 x 1.0 x 0.35 mm**

SOT1202




Fig 15. Package outline SOT1202 (XSON6)

X2SON5: plastic thermal enhanced extremely thin small outline package; no leads;  
5 terminals; body  $0.8 \times 0.8 \times 0.35$  mm

SOT1226




Fig 16. Package outline SOT1226 (X2SON5)

## 14. Abbreviations

**Table 11. Abbreviations**

Acronym	Description
CDM	Charged Device Model
DUT	Device Under Test
ESD	ElectroStatic Discharge
HBM	Human Body Model
MM	Machine Model

## 15. Revision history

**Table 12. Revision history**

Document ID	Release date	Data sheet status	Change notice	Supersedes
74AUP1G80 v.4	20120628	Product data sheet	-	74AUP1G80 v.3
Modifications:				
		• Added type number 74AUP1G80GX (SOT1226)		
		• Package outline drawing of SOT886 ( <a href="#">Figure 11</a> ) modified.		
74AUP1G80 v.3	20111129	Product data sheet	-	74AUP1G80 v.2
Modifications:				
		• Legal pages updated.		
74AUP1G80 v.2	20100915	Product data sheet	-	74AUP1G80 v.1
74AUP1G80 v.1	20061020	Product data sheet	-	-

## 16. Legal information

### 16.1 Data sheet status

Document status <sup>[1][2]</sup>	Product status <sup>[3]</sup>	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <http://www.nexperia.com>.

### 16.2 Definitions

**Draft** — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. Nexperia does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

**Short data sheet** — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local Nexperia sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

**Product specification** — The information and data provided in a Product data sheet shall define the specification of the product as agreed between Nexperia and its customer, unless Nexperia and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the Nexperia product is deemed to offer functions and qualities beyond those described in the Product data sheet.

### 16.3 Disclaimers

**Limited warranty and liability** — Information in this document is believed to be accurate and reliable. However, Nexperia does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. Nexperia takes no responsibility for the content in this document if provided by an information source outside of Nexperia.

In no event shall Nexperia be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, Nexperia's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of Nexperia.

**Right to make changes** — Nexperia reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

**Suitability for use** — Nexperia products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of a Nexperia product can reasonably be expected to result in personal injury, death or severe property or environmental damage. Nexperia and its suppliers accept no liability for inclusion and/or use of Nexperia products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

**Applications** — Applications that are described herein for any of these products are for illustrative purposes only. Nexperia makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using Nexperia products, and Nexperia accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the Nexperia product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

Nexperia does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using Nexperia products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). Nexperia does not accept any liability in this respect.

**Limiting values** — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

**Terms and conditions of commercial sale** — Nexperia products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nexperia.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. Nexperia hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of Nexperia products by customer.

**No offer to sell or license** — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

**Export control** — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

**Non-automotive qualified products** — Unless this data sheet expressly states that this specific Nexperia product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. Nexperia accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without Nexperia's warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond

Nexperia's specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies Nexperia for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond Nexperia's standard warranty and Nexperia's product specifications.

**Translations** — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

## 16.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

## 17. Contact information

For more information, please visit: <http://www.nexperia.com>

For sales office addresses, please send an email to: [salesaddresses@nexperia.com](mailto:salesaddresses@nexperia.com)

## 18. Contents

---

1	General description.....	1
2	Features and benefits .....	1
3	Ordering information.....	2
4	Marking.....	2
5	Functional diagram.....	2
6	Pinning information.....	3
6.1	Pinning .....	3
6.2	Pin description .....	4
7	Functional description .....	4
8	Limiting values.....	4
9	Recommended operating conditions.....	5
10	Static characteristics.....	5
11	Dynamic characteristics .....	8
12	Waveforms .....	11
13	Package outline .....	13
14	Abbreviations.....	19
15	Revision history.....	19
16	Legal information.....	20
16.1	Data sheet status .....	20
16.2	Definitions.....	20
16.3	Disclaimers.....	20
16.4	Trademarks.....	21
17	Contact information.....	21
18	Contents .....	22