


1 W wearable wireless power system based on STWBC-WA and STWLC04

Data brief



Features

- Wearable KIT characteristics:
 - 11 mm coil on Receiver
 - 20 mm coil on Transmitter
 - 1 Watt delivered on Receiver side
 - USB 5 V input
 - Foreign Object Detection (FOD) optional
 - Graphical interface for monitoring behavior
 - Total reference design
 - RoHS compliant
- STWBC-WA Wireless power transmitter:
 - Cost effective Half Bridge topology with integrated drivers
 - Optional Full Bridge configuration for 3 W applications
 - Active presence detector
 - 2-layer PCB to facilitate design
 - Turnkey solution or customizable via APIs
 - Parametric customization via Graphical interface

- STWLC04 wireless power receiver:
 - Output voltage: 5 V regulated voltage
 - Integrated high efficiency synchronous rectifier
 - Li-Ion/Li-Pol charger functionality
 - 4-layer PCB to facilitate design

Description

The STEVAL-ISB038V1 is a wireless battery charger evaluation kit designed for ultra-compact battery operated devices, such as wearable gears, smartwatches, Internet Of Things sensors, medical devices.

The kit supports wireless power transfer of 1 Watt over a 11 mm coil on the receiver side and 20 mm on transmitter side. The kit configuration delivers 1 Watt of power at the receiver side.

The Kit is configured to support low power (1 W) applications. The Kit can support up to 3 W applications by means of wider coils or by switching to full-bridge configuration on the transmitters (documentation available on KIT webpage on www.st.com).

The STWBC-WA transmitter is based on a cost-effective half bridge topologies (full-bridge optional) offers flexibility in terms of offering a powerful software API which allows to modify the behaviour of LED and GPIOs, as well as adding external interfaces via I²C and UART communication ports.

The STWLC04 is focused on 1 W protocol based on Qi. Digital control and precise analog control loops assure stable operation. I²C interface allows many parameters to be customized in the device and this configuration can be stored in the embedded NVM memory.

1 Continued description

The STWLC04 receiver can deliver the output power in the following modes:

1. as a power supply with configured output voltage
2. as a CC/CV battery charger with configurable charging current and voltage.

The full kit includes the STWBC-WA demo board; the STWLC04 demo board; the graphical interface to monitor the transmitter behavior; schematics, layout files and bill of materials.

Tools for the STEVAL-ISB038V1 are available on www.st.com for users to access runtime information such as delivered power and protocol status, and to adjust certain parameters.

2 Transmitter schematic diagrams

Figure 1: STEVAL-ISB038V1T transmitter control stage




Figure 2: STEVAL-ISB038V1T transmitter power stage





Figure 3: STEVAL-ISB038V1T USB to UART dongle



3 Receiver schematic diagrams

Figure 4: STEVAL-ISB038V1R receiver board





Figure 5: STEVAL-ISB038V1R USB-I²C dongle

4 Revision history

Table 1: Document revision history

Date	Version	Changes
03-Aug-2016	1	Initial release.

IMPORTANT NOTICE – PLEASE READ CAREFULLY

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2016 STMicroelectronics – All rights reserved