

ME500806

3-Phase Full-Wave Bridge Rectifier - 3-Phase Diode Bridge Module.

Powerex Power Semiconductors

V(RRM)(V) Rep.Pk.Rev. Voltage=800

I(O) Max.(A) Output Current=60

@Temp (jãC) (Test Condition)=90

@V(R) (V)(Test Condition)=800

I(RM) Max.(A) Pk. Rev. Current=1.5m

@Temp. (jãC) (Test Condition)=125

I(FSM) Max.(A) Pk.Fwd.Sur.Cur.=1.0k

V(FM) Max.(V) Forward Voltage=1.3

@I(FM) (A) (Test Condition)=60

@Temp. (jãC) (Test Condition)=25

Package=MODULE-var

Military=N